



單位：mm

軸徑	代碼	華司尺寸				安裝尺寸		
		$d \begin{smallmatrix} +0.25 \\ 0 \end{smallmatrix}$	$D \begin{smallmatrix} 0 \\ -0.25 \end{smallmatrix}$	$T \begin{smallmatrix} 0 \\ -0.07 \end{smallmatrix}$	$J \pm 0.12$	$a \begin{smallmatrix} +0.4 \\ +0.1 \end{smallmatrix}$	$t \begin{smallmatrix} 0 \\ -0.25 \end{smallmatrix}$	$D1 \begin{smallmatrix} +0.12 \\ 0 \end{smallmatrix}$
10	LX-10W	12	24	1.42	18	1.5	1.1	24
12	LX-12W	14	26		20			26
14	LX-14W	16	30		23	2		30
16	LX-16W	18	32		25			32
18	LX-18W	20	36		28	3		36
20	LX-20W	22	38		30			38
22	LX-22W	24	42		33			42
24	LX-24W	26	44		35			44
25	LX-25W	28	48		38	4		48
30	LX-30W	32	54		43			54
35	LX-35W	38	62	50	62			
40	LX-40W	42	66	54	66			
45	LX-45W	48	74	61	1.6		74	
50	LX-50W	52	78	65			78	
60	LX-50W	62	90	76		90		

備註：應該用栓或沉頭孔螺絲把華司固定在底座上

如何訂購： 例 LB-20 W: 輕徑 / 華司

標準滑板 LX-P

單位：mm

代碼	長度 $\begin{smallmatrix} +1.0 \\ 0 \end{smallmatrix}$	寬度 $\begin{smallmatrix} +2.0 \\ 0 \end{smallmatrix}$	厚度 T $\begin{smallmatrix} 0 \\ -0.1 \end{smallmatrix}$
LX-150P	500	90	1.45
LX-200P	500	100	1.95
LX-250P	500	100	2.45

如何訂購： 例 LX-200 P: 厚度 / 滑板